

GIB760v0

TECHNICAL DOCUMENT- CONTROL GEAR

Supplier's name or trade mark:	MEGAMAN GmbH
Supplier's address	Halskestraße 22-26, AircomParc A140880 RatingenGermany

Model identifier

Model Number	GIB760v0
General description	Input: AC220~240 Output: 5.2W DC75 DC 69mA

Technical Document

Maximum output power	5.2W
Type of light source(s)	LED
Efficiency in full-load	87%
No-load power (Pno)	not applicable
Standby Power (Psb)	N/A
Networked Standby Power (Pnet)	N/A
Outer dimensions in mm	
Height	15
Width	143
Depth	193
Mass in grams	13.6
Standards Compliance	EN 61347-1:2015 & EN61347-2-13:2014

Warning

A list of compatible dimmers shall be provided on the website www.megaman.cc

MEGAMAN | WEEE - Green Room | LED, Energy-efficient & Eco-friendly Lighting, Restriction of Hazardous Substance
<https://www.megaman.cc/resources/green-room/weee>

Identification and signature

Model no.:FIB76000v0-ps,FIB76100v0-ps

Light source model identifier:SIB760v0830,SIB760v0840,SIB761v0830,SIB761v0840

Light source: Removable

SIB760v0830,SIB760v0840

I in: 75mA

U in 69VDC

SIB761v0830,SIB761v0840

I in: 95mA

U in 77VDC

	<p>Step1: Use a flat-blade screwdriver to pry open the sensor cover from the contact surface of the infrared sensor and the diffuser</p>  	<p>Step2: Remove the sensor</p> 
<p>Step3: Use a flat-blade screwdriver to pry open the side cover close to sensor side, and pull out the light source board and drive module</p>  	<p>Step4: Pull out the light source output line, separate the light source .</p> 	<p>Step5: Take the wiring terminal out of the positioning column, and take out the drive along the arrow in picture 2</p>   